



**Generating Set Base Frame - Diesel** 

# GE.BD.2550/2280.BF+011

1500 rpm - Threephase - 50Hz - 400V Automatic panel without switching on board



# **Standard equipment**



Exhaust manifold protection Exhaust flexible expansion joint Silenced muffler -15dB(A)

# Fuel Supply

Fuel connections Automatic shutdown system for low fuel level

### **A** Handling

n.4 lifting hooks integrated into the bearing structure

Anti-vibrating mounting pads

# Engine

High coolant temperature and low oil pressure shutdown

Oil pressure and coolant temperature gauge (only with QPE or +14 variant)

Oil change pump

Engine liquids (oil and antifreeze)

Tropicalized radiator

Rotating parts protection

Electronic speed governor

Radiator level sensor

### Alternator

**AVR Automatic Voltage Regulator** AVR Pre-arranged for parallel Bi-phase sensing AVR Impregnation for marine environment

# Panel & connection

**Emergency Stop button** Magnetothermal circuit breaker on alternator board Cable output from side IP44 wiring Start-up battery (pre-charged) Grounding point

# Documentation

CE conformity declaration User and Maintenance manual Wirings diagrams

### Normatives

All Generating sets are compliant to CE Marking 2014/30/UE Electromagnetic compatibility 2000/14/CE Noise Emission for outdoor use Factory-designed systems built according to ISO 9001:2015 CEI EN 60204-1:2018 - Electrical equipment of machines















# **Primary data**

Speed	RPM <b>1500</b>
Frequency	Hz <b>50</b>
PRP	KVA 2280
PRP - Prime power	KW 1824
LTP - Standby power	KVA <b>2550</b>
LTP - Standby power	KW <b>2040</b>
Standard Voltage	V 400/230
Current	A 3294,8
Voltage for current calculation	V 400
COSFI	0,8 0,8
Circuit-breaker rated current	A 4000
Circuit-breaker poles	Magnetothermal switch on the alternator board  N 4P
Circuit-breaker poles  Fuel Consumption	
Circuit-breaker poles  Fuel Consumption  TYPE	N 4P
Circuit-breaker poles  Fuel Consumption  TYPE  Standard Fuel Tank capacity	N 4P  Diesel
Fuel Consumption  TYPE  Standard Fuel Tank capacity  Fuel consumption at 100% load	Diesel  // No tank
Fuel Consumption  TYPE  Standard Fuel Tank capacity  Fuel consumption at 100% load  Fuel consumption at 75% load	Diesel
Type  Circuit-breaker poles  Fuel Consumption  TYPE  Standard Fuel Tank capacity  Fuel consumption at 100% load  Fuel consumption at 75% load  Fuel consumption at 50% load  General data	Diesel

Rated capacity	Ah	4x180	
Auxiliary Voltage	V	24	
Exhaust gas temperature	°C	550	
Exhaust gas flow	l/s	7141	
Combustion air flow	l/s	2383	

# Weight and Dimensions

Dimensions (L x w x h)	cm	610x220x255
Weight with liquids (excluding optionals and fuel)	Kg (+/-3%)	17764







Factory		Baudouin
Model		12M55G2550/5
Emissions stage		Stage 0
Speed governor		Electronic
Radiator	°C	50
Cooling	Tipo	liquid (water + 50% Paraflu11)
Active net power	Kwm	1900
Nominal net power	CV	2581
Cycle	Tipo	4 strokes
Aspiration	Tipo	Turbo
Numbers of cylinders	N	12
Cylinders arrangement		V
Bore	mm	180
Stroke	mm	215
Total displacement	lt	65,65
Engine oil features		15W40-API CI-4/CH-4 ACEA E5-E7
Total oil capacity	lt	480
Total coolant capacity	It	560
ISO 8528-5 class		G2

The emission levels of the exhaust gas are indicated in the engine technical datasheet. Any changes due to more restrictive regulatory adjustments are excluded.

# Alternator

\* May vary based on stock availability. However, a primary brand will be used.

Factory	Stamford
Model	PI734H
Single-phase Range	KVA 2325
Voltage Regulator (voltage accuracy)	+/- % 1
Poles	N° <b>4</b>
Phases	N° 3+N
Standard windings connection	Star Series
Stator/rotor impregnation	H (Outdoor Temp 40°C)
Efficiency	% 96,2
Engine coupling	Elastic disk
Short circuit current	>= 300% (3ln)
Protection degree	IP 23
Cooling system	Self ventilating
Maxium overspeed	rpm <b>2250</b>
Waveform distortion	% <5
Exciter	PMG

# Standard operating environmental conditions

Ambient temperature	°C	25
Relative Humidity	%	30
Max altitude	mt	1000






### ₩ GE.BD.2550/2280.ST.BF+011

# **Control Systems on board QPE-C-SC-3F-V1**





operating scheme - schema di funzionamento

# 

The QPE-C control panel represents the evolution of the panel for the control and management of the gen set. With its microprocessor logic it is able to meet any user requested features. The dual operation mode manual and automatic guarantees to every type of functionality protection, analysis and control of the generating set in order to make the management easy and efficient. Variant without transfer switch on board. ATS panel type QC as optional. The panel manages the QC panels directly or any other ATS panel.

# Mechanical features

	55
--	----

# Battery charger

Model	ODEO	10	ELCOS - CB1
Maximum output current	GUIU	Α	2,5
Output DC voltage (selectable)		Vdc	12-24
Input AC voltage (selectable)		Vac	220-260
Frequency		Hz	50-60

# Data Communication

Data connection port	RS-485
Communication protocol	Mod-bus RTU-8N1

# Remotable functions in terminal box

GS start
Genset contactor close/open command (1)
Common Alarm - DC output
GS start with key in OFF position (Only in MRS mode)

GS lock
Mains contactor close/open command (2)
GS test without load
Programmable output - Volt free output





Model MC4 Operating mode AMF - MRS

#### **Specifics**

#### **Applications**

**Emergency to the Mains** Stand-alone Construction site/Rental Self-production

#### **ENGINE MEASURES**

Fuel tank level % Engine oil pressure BAR (1) Engine Coolant temperature °C (1) Total run time Partial run time Hours to maintenance

Battery voltage

Battery charging voltage Start-ups counter

Engine speed (2)

Engine Oil temperature (2)

Cooler temperature (2)

Engine oil level (2)

Engine coolant level (2)

Engine coolant pressure (2)

Turbo pressure (2) Fuel Consumption (2)

Tank autonomy - hrs (5)

Fuel remaining quatity (5)

Fuel used quantity (5)

#### **ALTERNATOR MEASURES**

Generator Voltage L1, L2, L3 Generator Voltage L1-N, L2-N, L3-N Generator frequency Generator current L1, L2, L3 Generator Apparent Power kVA Generator Active Power kW Generator Reactive Power kVAR Generator accumulated power kWh

### Power factor Cosfi **MAINS MEASURES**

Mains voltage L1, L2, L3 Mains voltage L1-N, L2-N, L3-N Mains frequency

#### **COMMUNICATION PORTS**

Can-bus port RS485 port with Mod-bus RTU communication RS232 port for display connection USB port for parameters saving and firmware update

#### **EQUIPMENT**

Microprocessor Logic Back-lit display Programmable from display 16 event log Multiple display languages STOP button START button TEST button Reset alarm button Alarm mute button Fuel transfer pump activation button Glow-plug activation button

#### PRE-ALARMS/ ALARMS

Common Alarm Fuel reserve (pre-alarm) Low fuel level (alarm) Tank overflow

Charge alternator failed (dinamo)

Low oil pressure (pre-alarm) (1) Low oil pressure (alarm)

Oil sensor failed (alarm)

High coolant temperature (pre-alarm) (1)

High coolant temperature (alarm)

Low coolant temperature (pre-alarm)

Low water level (1) Water in fuel (1)

Battery undervoltage

Battery overvoltage

GS failure to start

GS failure to stop

Can-bus Failure

No Can-bus communication Genset overload L1, L2, L3 phases

Genset short circuit

Genset overvoltage

Genset undervoltage

Genset high frequency Genset low frequency

overspeed

Reverse power

Earth fault (pre-alarm)

Earth fault (alarm)

Block from password

CAN communication Failed

Maintenance request Emergency button pressed

Remote emergency active

Forced stop

External battery failed

Fuel theft

Genset negative phase sequence

Mains negative phase sequence

Fuel theft protection

### **VISUALIZATIONS ON CONTROL**

#### MODULE/DISPLAY

Pre-alarms

Alarms

Engine measures

Alternator measures

Mains measures

Date and time

Operating mode

Genset status

Mains status

Mains contactor status

Genset contactor status

Digital Input and Output status

Grounding current mA (3)

Grounding current threshold mA (3)

Delay time of differential protection (3)

Glow plugs status

#### **CONTROL MODULE FUNCTIONS**

Automatic start and stop when the Mains Fails (7)

Remote Start and Stop

Remote Start and Stop with key in OFF position

Manual Start and stop

Emergency stop button on panel board

Remote emergency stop

Remote lock

Remote test without load

Remote test on load

Scheduled start-ups

MODBUS commands (Start, Stop, Reset, Test)

#### CONTROL MODULE SPECIAL FUNCTIONS (on demand)

Automatic charging of an external battery Dummy load (4)

Load shedding (4)

Redundant starter motor management

Fuel monitoring GS battery Load test

Idle mode

Service phone number indication

Variable speed Generator Master / Slave mode

(1) Present with the sensor installed on engine (2) Present according to the engine equipment and to the ECU type (ECU - Canbus)

(3) Present only with the residual current device mounted on genset board

(4) Present with optional expansion modules

(5) Present with special function activated

(6) Only with the optional of the automatic fuel refilling system on board

(7) Only in AMF mode



#### **OPTIONAL**

٥	Fuel	Sup	ply
---	------	-----	-----



O.G-ACO-AT-C3V-03 External fuel tank connections with 3-way valve for supply from internal or external tank (750/3000 kVA)





**O.G-ALT-AL-COTE-01** Temperature control unit up to 4 x PT100 probes for MC4 management



O.G-ALT-AL-GEL-07 Joint and bell housing for double-bearing coupling (BF Gen Sets 1700/3000 kVA)



Anti-condensation heater 230 V (on Stamford from 22000 kVA to 3000 kVA)



O.G-ALT-ST-AVR-MX321 Stamford MX321 automatic voltage regulator with PMG (Check dimensions)



O.G-ALT-ST-AVR-MX341 Stamford MX341 automatic voltage regulator with PMG (Check dimensions)



O.G-ALT-ST-BIS-04 Additional cost for double-bearing alternator (select also joint and bell housing code) from 1900/3000 kVA



**O.G-ALT-ST-PT100-1CU** 1 x PT100 probe on bearing (80/3000 kVA)



or. 3 RTD-PT100 probes on stator windings



O.G-ALT-ST-PT100-6AV nr. 3+3 RTD-PT100 probes on stator windings (80/3000 kVA)



O.G-ALT-ST-RIGU-01 Diode Failure Detector (DFD) mounted on the alternator. Alarm contact available into the panel





O.G-BAT-DOB-07 Redundant battery kit for Gen Sets 1900/3000 kVA

### Container



CONTAINER-30HC-LT-02 Insulated Container 30' HC - LT Version - Standard GREY RAL 7015, Dim. cm. 913 x 244 x 290H - (1900/3000 KVA BF version)



CONTAINER-40HC-75D-03

Soundproofed Container 40' HC - Standard GREY RAL 7015, acoustic isolation 75 dBA at 7mt. (+/-3). Dim. cm. 1.219 x 244 x 289H - (1900/3000 KVA BF version)





₩ GE.BD.2550/2280.ST.BF+01

mili	TESTIT	Trong
		30
		133

**CONTAINER-40HC-LT-02** 

Insulated Container 40' HC - LT Version - Standard GREY RAL 7015, Dim. cm. 1.219 x 244 x 289H - (1900/3000 KVA BF version)



O.CO-GR-VE-ESP-02

Frontal vertical ejection grilles for GE from 750 to 3000 kVA

### Electrical on board



O.G-USP-SW-MOT.1700-3000

Motorization switch mounted on alternator for Ge 1700/3000 Kva - (for variant +11)

O.Q-QBM-BMIN-230V-02

Additional price for 230V minimum voltage coil on MCCB both on the control panel and on the alternator (check feasibility)

O.Q-QBM-CPI-BEN-01

Permanent insulation controller for IT networks up to 230V / 400V. BENDER IR423-D4-1. Adjustable threshold  $10 \div 300$  kohm. (2 DIN rail modules - check feasibility)



O.Q-QPE-485.CONV-LAN

Converter 485/LAN for QPE-C, QLE-B panel



O.Q-QPE-485.CONV-USB

Converter 485/USB for QPE panel

O.Q-QPE-DIS-MS.01

MASTER/SLAVE device for QPE panel

O.Q-QPE-K-DIF

Differential protection adjustable for the MC4

O.Q-QPE-MD-QPE-C

GSM remote management modem for QPE panel



O.Q-QPE-POT-VOLT

Internal potentiometer for voltage regulation - available only for variant +10/+11



O.Q-QPE-PR-QPE-C

Remote panel for QPE-C, QLE-B - available only for variant +10/+11



O.Q-QPE-QBM-COM-AMF25

Option with QBM COMAP AMF25 controller on board instead of QPE



O.Q-QPE-QBM-DSE-7320

Option with QBM DSE7320 controller on board instead of QPE.



O.Q-QPE-RIL-16RELE

16-relay module for QPE panel



O.Q-QPE-RX8-QPE-C

Start-stop radio control with max. radius 500 mt indoors and 5 km outdoors (for QPE panel).



O.Q-QPE-SAS-02

Auto Start-Stop at load request (QPE, QLE panels)



O.Q-QPE-SCD-01

Anti-condensation heater inside the panel



O.Q-QPE-TG-EVO-GPS-3G

QC5.4000A

Test



3) <b>EL</b>	CO5 GENERATORS	TALY
		₩ GE.BD.2550/2280.ST.BF+011
	O.Q-QPE-SEL-50-60	Switch selector 50Hz 400V / 60Hz 480V
	O.Q-QPE-TG-EVO-GPS-2G	Remote management system via LAN/GSM 2G with WEB application and GPS location system

Remote management system via LAN/GSM 3G with WEB application and GPS location

1		system
<b>2</b>	O.Q-QPE-TG-QPE-C	Remote management software via LAN for QPE-C, QLE-B panel compatible with Windows XP and 7

C Engine	

O.G-MOT-K-40C-08	Engine liquids suitable for -40°C ambient temperature for Gen Sets 1800/3000 kVA		
O.G-MOT-MAG-07	Dual starter motor for Gen Sets 1700/2500 kVA (engine configuration to be checked)		
O.G-MOT-SC-AC-EL-06	Super hot engine heater 230V with thermostat on board for Gen Sets 1250/3000 kVA		

O.G-MOT-SC-AC-WE-04	Webasto diesel-operated water pre-heater (1250/3000 kVA)

O.G-MOT-SE-LR-03	Radiator coolant level	sensor from 750 to 3000 kVA	ш	ОЦТ
JIC		$\cup$ $\square$ $\cup$ $\square$		$\Box\Box\bot$

# ATS Panels Separate ATS panel, 4000A motorized change-over (2700 kVA 400V) Dim. $260 \times 100 \times 190$

cm - 700 kg. (ex QC5.2500)

QCP5.4000A	Separate ATS switching panel, with Lovato ATL 610 control unit, for variant +014,ABB motorized change-over 4000A 4P (2700kva 400V) and compartment for power cables inlet

** Parallel panels				
APM Automatic Parallel Module Comap InteliVision5 logic with motorized breaker (4000A) for gen set from 2300 to 2800 kVA.Dim. cm. $100 \times 100 \times 190H$ .				

	QP.APM9.4000A	for gen set from 2300 to 2800 kVA.Dim. cm. 100 x 100 x 190H.		
Exhaust				
	O.G-SCA-MR-11	nr. 2 Residential mufflers -35 dBA (2300/3300 kVA)		

FAT - Factory Acceptance Test for single Gen Set from 2000 to 3000 kVA according to o standard procedures in Elcos factory (max 2 hours - max 4 people - max 1 hour of operation)	MS.CP-LT-06
---	-------------





200	<b>GE.BD</b>	2550	/2280	STI	BF+	01	1
	UL.DD		/		יו וש	$\sim$ 1	- 1

Under the second	MS.CP-SP-06	FAT - Factory Acceptance Test for single custom Gen Set from 2000 to 3000 kVA max 4 operating hours or parallel system up to 4 units for 1 operating hour, in Elcos factory (max 4 hours - max 4 people )
	MS.CP-SP-MV-04	FAT - Factory Acceptance Test for single custom Gen Set from 2000 to 3000 kVA max 4 operating hours or parallel system up to 4 units for 1 operating hour, in Elcos factory (max 4 hours - max 4 people )
	MS.CP-ST-06	FAT - Factory Acceptance Test for single Gen Set from 2000 to 3000 kVA according to our standard procedures in Elcos factory (max 4 hours - max 4 people - max 2 hour of operation)
	MS.CP-ST-MV-04	FAT - Factory Acceptance Test for single Gen Set from 2000 to 3000 kVA according to our standard procedures in Elcos factory (max 2 hours - max 4 people - max 1 hour of operation)
	MS.TV-ST-02	Vibration test on 10 points with certificate for single Gen Set from 275 to 3000 kVA
<b>⇔</b> Vari		
	O.G-VAR-CAT-03	Toolbox for ordinary maintenance.
	O.G-VAR-PUN-TER-01	Round earth spike, diam. 20 mm, height 1.5mt, galvanized, complete with clamp and 3m yellow/green cable model FS17 1x35mm <sup>2</sup> with cable lugs.
	O.G-VAR-PUN-TER-02	Cross-shaped earth spike, height 1.5mt, galvanized, complete with clamp and 3m yellow/green cable model FS17 1x35mm <sup>2</sup> with cable lugs.
1 Itm	O.G-VAR-SFA-09	Aspiration / expulsion sound attenuators -25dBA for Gen Sets 1400/3000 kVA (Supplied

# **энерго**континент

#### **PRP**

Engines of this rating provide unlimited hours of usage in a variable load application. The average load factor should not exceed 70% of the engine's prime power rating with a maximum number of 500 operational hours at 100% prime power rating. An overload capability of 10% is available, however, is limited to a period of 1 in every 12 hours

O.G-VAR-SFA-09

### **LTP**

Limited-time running power is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500h of operation per year with the maintenance intervals. The overload is not allowed.